

# SUNLITE-BC

sunlite

Sunlite USB-DMX controller



## Overview

Featuring 256 DMX channels, the new SUNLITE-BC includes SUT (Smart Upgrade Technology) and is upgradable to 512 channels or more using optional Art-Net universes.

Compatible with Sunlite Suite 2 and 3 running in Express Mode, with the option to upgrade to Full Mode, the Sunlite-BC offers the most affordable way to access the power of Sunlite.

Each interface comes with internal flash stand-alone memory, allowing for simple programmed scenes to be run without a computer.

[www.sunlitepro.com/hardware.htm](http://www.sunlitepro.com/hardware.htm)

## Key Features

- USB Type-C connection
- Compatible with Sunlite Suite 2 & 3  
[www.sunlitepro.com/download.htm](http://www.sunlitepro.com/download.htm)
- 256 DMX512 channels in live mode \*
- 128 DMX512 channels in stand alone \*
- Buttons for changing scenes and dimmer in standalone mode

## \* SUT (Sunlite Upgrade Technology)

The Sunlite-BC is compatible with SUT (Sunlite Upgrade Technology). If you need more than 256 channels or need Full Mode, SUT allows an easy upgrade online. You can also purchase software licences for any other Nicolaudie Group software. Free 30 days trials on most upgrades. Find out more at [store.dmxsoft.com](http://store.dmxsoft.com)

## Technical Data

<b>Input Power</b>	5-5.5V DC 0.6A
<b>Output Protocol</b>	DMX512 256 channels Live * 128 channels Standalone *
<b>Software Compatibility</b>	Sunlite Suite 3 Express Sunlite Suite 2 Express ESA2 Other packages via SUT *
<b>Connections</b>	USB Type-C, XLR3
<b>Memory</b>	internal flash
<b>Environment</b>	IP20. 0°C - 50°C
<b>Buttons</b>	2 buttons to change scene + 1 activate dimmer
<b>Dimensions</b>	90x50x37mm Complete Package 102x73x45mm
<b>OS Requirements</b>	Windows 7/8/10 64bit
<b>Standards</b>	EC, EMC, ROHS

## HardwareManager

Included with your software is a tool called *HardwareManager*. Use this to check that you are

running the latest firmware version everytime you update to the latest software version.