



FLASH 401 is an audience blinder and strobe with four 100 watts Warm White COB LED sources. Every 2 LEDs are in an independent housing that can be rotated and directed easily. Each of the 4 LEDs is controlled separately adding a dynamic chase pixel mapping effect alongside the blinder and electronic strobe effect. It delivers a powerful output making it ideal for any size indoor stage, clubs and entertainment lighting installation.

SOURCE Light source: 4 x 100 watts LED
Color temperature: 3200k
LED life expectancy: 50,000 Hrs.

OPTICAL SYSTEM Beam angle: 40°

DYNAMIC EFFECTS Dimmer: Linear adjustment
Electronic strobe
4 zones control

CONTROL & PROGRAMMING Control protocols: DMX, Sound, Master-Slave, Auto Run
Control channels: 2, 8 CHs

ELECTRICAL Input voltage: AC100-240V/50-60Hz
Power consumption: 400 watts

CONNECTIONS DMX connections: 3 pin and 5 pin XLR In/Out male and female
Power connections: PowerCon In/Out

PHYSICAL Dimensions: 400 x 400 x 200mm
Net weight: 11 Kg
Color: Black
Housing: Aluminum
IP rating: 20

Dimensions

