



FLASH 402 is an IP65 Outdoor high-powered audience blinder and strobe. It is powered with four 100 watts Warm White COB LED sources housed in 4 independently rotatable heads. Each of the 4 LEDs is controlled separately adding a dynamic chase pixel mapping effect alongside the blinder and electronic strobe effect. It delivers a powerful output making it ideal for any scale outdoor stage and entertainment applications.

SOURCE Light source: 4 x 100 watts LED
Color temperature: 3200k
LED life expectancy: 50,000 Hrs.

OPTICAL SYSTEM Beam angle: 50°
4 Rotatable Heads

DYNAMIC EFFECTS Dimmer: Linear adjustment
Electronic strobe: 1-30 Hz
4 zones control

CONTROL & PROGRAMMING Control protocols: DMX, Auto, Sound
Control channels: 4, 8 CHs
LCD Control Panel

ELECTRICAL Input voltage: AC100-240V/50-60Hz
Power consumption: 450 watts

CONNECTIONS DMX connections: On Cable 3 pin XLR In/Out
Power connections: On Cable Waterproof 3 pin In/Out

PHYSICAL Dimensions: 450 x 420 x 270mm
Net weight: 12 Kg
Color: Black
Housing: Aluminum
IP rating: 65

Dimensions

